

## **LPAR-1Q :**

### **DMX channel's functions and their values (4 DMX channels):**

| Mode/Channel | Value | Function  |              |
|--------------|-------|---|--------------|
| 1            | 0-255 | <b>Red LED:</b><br>Red ( 0-Black , 255-100% Red )       | LED红色从0~100% |
| 2            | 0-255 | <b>Green LED:</b><br>Green ( 0-Black , 255-100% Green ) | LED绿色从0~100% |
| 3            | 0-255 | <b>Blue LED:</b><br>Blue ( 0-Black , 255-100% Blue )    | LED蓝色从0~100% |
| 4            | 0-255 | <b>White LED:</b><br>White ( 0-Black , 255-100% White ) | LED白色从0~100% |